

Ag59800-LPB

High Efficiency SMT Class 8 Power-over-Ethernet Module



Features

- > 95% efficient 100W DC/DC converter
- IEEE802.3bt class 8 PD (PoE++) for up to 89W output applications
- > 12V and 24V variants available
- Low output ripple & noise
- Overload, short-circuit and thermal protection
- Adjustable output voltage
- Industrial temperature range
- > Minimal external components required
- IEEE802.3bt compliant, compatible with IEEE802.3at and IEEE802.3af
- Compact Surface mount package size 51mm x 30mm x 15mm
- > 1500Vdc isolation (input to output)
- > Silvertel "design-in" assistance
- Designed and manufactured in the UK

Description

Ag59800-LPB series Power-over-Ethernet (PoE++) modules are designed to extract power from a conventional twisted pair Category 5 Ethernet cable, conforming to the IEEE802.3 PoE standard, with full compatibility with the IEEE802.3bt, IEEE802.3at and IEEE802.3af amendments.

The Ag59800-LPB is pre-configured as a Type 4 Class 8 device, requesting a minimum of 90W of power from the PSE, with nominal output voltages of 12V or 24V.

The high efficiency DC/DC converter can achieve up to 95% efficiency and operates over a wide input voltage range with a low ripple and low noise output. The DC/DC converter also has built-in output overload, output short-circuit and over-temperature protection and provides a 1500Vdc (input to output) isolation barrier, as required by the IEEE802.3 specification.

High Efficiency SMT PoE++ Module

Table of Contents

1	Pro	oduct Overview	. 3
	1.1	Ag59800-LPB Product Selector	. 3
	1.2	Package Format	. 4
	1.3	Pin Description	. 4
	1.4	Typical Connections	. 5
2	Inp	put	. 6
	2.1	PD Signature	. 6
	2.2	Power Classification	. 6
	2.3	PSE Type Detection	. 7
3	Ou	tput	. 8
	3.1	Maximum output power	. 8
	3.2	Output Voltage Adjust Setting	. 9
	3.3	Output Filtering	10
4	Eff	iciency	10
5	Ор	erating Temperature Range	11
	5.1	Thermal Considerations	11
6	Pro	otection	14
	6.1	Input Protection	14
	6.2	Output Back Feed Protection	14
	6.3	Output Short Circuit Protection	14
	6.4	Thermal Protection	14
7	lso	lation	15
8	EM	IC	15
9	So	Iderability	16
	9.1	Solder Profile	16
1() Ele	ectrical Characteristics	17
	10.1	Absolute Maximum Ratings	17
	10.2	Recommended Operating Conditions	17
	10.3	DC Electrical Characteristics	18
11	l Pa	ckage	19
12	2 Pa	ckaging	20
13	B Ore	dering Code	20

Table of Figures

Figure 1: Block Diagram	3
Figure 2: Ag59800-LPB Package Format	4
Figure 3: Typical System Diagram	5
Figure 4: Physical Layer Detect Configuration.	7
Figure 5: Output Voltage Adjustment	9
Figure 6: Output Filter	10
Figure 7: Efficiency	10
Figure 8: Thermal Relief	12
Figure 9: Thermal Interface Application Region	12
Figure 10: Additional Heatsinking	13
Figure 11: Input Protection	14
Figure 12: Typical Connection Diagram	15
Figure 13: Package Dimensions	19
Figure 14: Land Pattern	19
-	

1 **Product Overview**

1.1 Ag59800-LPB Product Selector

Part Number ¹ Output Voltage		Output Power	Marking ²	Package
Ag59812-LPB 12V		100W/DC/DC Convertor3	ab12c	смт
Ag59824-LPB	24V	TOOVY DC/DC Converters	ab24c	SIVII

Note 1: Complies with the European Directive 2011/65/EU for the Restriction of use of certain Hazardous Substances (RoHS) including Directive 2015/863 published in 2015, amending Annex II of Directive 2011/65/EU. Moisture Sensitive Level 1 and HBM 1.

Note 2: Located on the transformer.

The first letter, a, indicates the week as A-Z with uppercase being weeks 1-26, lower case weeks 27-52. The second letter, b, indicates the year in uppercase A-Z starting from 2020. The two digits are the nominal output voltage, The final letter, c, is a Silvertel reference. Note 3: Usable output power limited by PSE output power and transmission losses



Table 1: Ordering Information

Figure 1: Block Diagram

High Efficiency SMT PoE++ Module

1.2 Package Format



Figure 2: Ag59800-LPB Package Format

1.3 Pin Description

Pin #	Name	Description
1	V _{IN-}	POE Direct Input - . This pin connects to the negative (-) output of the POE input bridge rectifiers.
2	TYP2-DET	Type 2 Detect Output. This pin indicates if an IEEE802.3at PSE is supplying power to the Ag59800-LPB; see Section 2.3 for more details.
3	TYP3-DET	Type 3 Detect Output. This pin indicates if a IEEE802.3bt Type 3 or Type 4 PSE is supplying power to the Ag59800-LPB; see Section 2.3 for more details.
4	Vour	Positive DC Output. This pin provides the positive regulated output from the
5	V OUT+	Ag59800-LPB.
6		Negative DC Output. This pin provides the negative regulated output from the
7	VOUT-	Ag59800-LPB.
8	ADJ	Output Adjust. The output voltage can be adjusted from its nominal value, by connecting an external resistor from this pin to either the +VDC pin or the -VDC pin.
9	V _{IN+}	POE Direct Input + . This pin connects to the positive (+) output of the POE input bridge rectifiers.

Table 2: Pin Description

1.4 Typical Connections

The Ag59800-LPB only requires a few external components - the bridge rectifiers on the V_{IN} input are to conform to the input polarity protection requirement. The output capacitor (C1) connected across the output is required for correct operation of the DC/DC converter. For optimal stability, this capacitor must be positioned as close to the output pins as possible.

The output capacitance can be a low-cost electrolytic capacitor as shown in Figure 3; it does not need to be a low ESR type for operation in temperatures down to 0°C. But if ambient temperatures below 0°C are expected, a capacitor that retains a moderately low ESR and the minimum capacitance is essential for operation; Polymer Aluminium Solid Electrolytic Capacitors are ideal for below zero ambient temperature applications.

The output voltage can be adjusted by simply connecting a resistor between the ADJ pin and either the +VDC Pin or the -VDC pin, see section 3.2 Output Voltage Adjust Setting.



Figure 3: Typical System Diagram

2 Input

The Ag59800-LPB has two input pins VIN+ and VIN-, these should be connected to the outputs of two external bridge rectifiers (see Figure 3: Typical System Diagram). This allows the Ag59800-LPB to be compatible with Power Sourcing Equipment (PSE) that utilise any of the permissible power source polarity configurations.

The Ag59800-LPB is designed to be powered by any compliant IEEE802.3 PSE, such as Silvertel's Ag6810.

2.1 PD Signature

The Ag59800-LPB complies with the IEEE802.3 specifications and provides the required signature and control circuitry within. When the inputs are connected to a PSE, they will automatically present a Powered Device (PD) signature to the PSE (when requested). The PSE will then recognise that a valid PD is connected to that line and progress to the classification and powering stages.

2.2 Power Classification

The Ag59800-LPB is a fixed Type 4 - Class 8 PD requesting 90W of power from a compliant IEEE802.3 Type 4 PSE by displaying the correct class pulse response shown in Table 3 below. If the Ag59800-LPB is connected to a Type 1 or Type 2 PSE, the PSE will recognise the Class request as a valid request beyond maximum output and default to its highest output classification power level, and supply 15.4W for a type 1 PSE and 30W for a Type 2 PSE.

Requested Class	Class Pulse Count	Pulse 1&2 Classification Current (mA)	Pulse 3+ Classification Current (mA)	PSE Output Power (W)	Min. Available PD Power (W)	IEEE Spec. Amendment
0	1	<5	N/A	15.4	12.75	
1	1	10	N/A	4	3.84	902 2of
2	1	20	N/A	7	6.49	002.381
3	1	30	N/A	15.4	12.75	
4	2 or 3	40	40	30	25.5	802.3at
5	4	40	<5	45	40	
6	4	40	10	60	51	000 0ht
7	5	40	20	75	62	002.301
8	5	40	30	90	71.3	

Table 3	3: C	lassif	ication	Table
---------	------	--------	---------	-------

2.3 **PSE Type Detection**

The IEEE802.3 specification stipulates that if a device detects it is connected to a PSE that is not capable of providing the full requested power level, the device should remain in a reduced power mode and/or indicate to the user that the device is under powered. To complete the protocol (and conform to the IEEE802.3 specification) the controller should then confirm that it is a Type 3 PD over the Data Link Layer^{*}.

To achieve this, the Ag59800-LPB monitors the detection and classification sequence to determine the type of PSE that performed the signature and classification. The module then uses the two type detection output pins, TYP2-DET and TYP3-DET, to flag to either the application circuitry or the user the detected PSE type to either adjust the peak power draw of the application or to inform the user that the device is under powered and may power cycle.

When the PSE type has been detected, the relevant pins will pull low from Vin+; this can be used to drive an LED or an Optocoupler as shown in Figure 4.





Detected PSE Type	TYP2-DET output	TYP3-DET output
1	High	High
2	Low	High
3	High	Low
4	Low	Low

Table 4: Type Detect Output Table

^{*} There are several PSEs (including Cisco) that will only deliver ≤15.4W until they receive confirmation over the Data Link Layer.

V1.2 May 2025

High Efficiency SMT PoE++ Module

If the Ag59800-LPB detects a greater than three Event Physical Layer classification, the switch will close and Opto2 will turn ON and Opto1 will be OFF. Opto2 will pass this signal across the isolation barrier and the output collector can be connected to a controller (with a pull-up resistor connected to the controller's power rail). When Opto2 is ON the collector (output) will be Logic 0, the controller will then know that the PSE is capable of delivering 60W.

If the Ag59800-LPB detects a Single Event Physical Layer classification, both Opto1 and Opto2 will be OFF and the output collectors will be Logic 1 (via pull-up resistor). The controller should then assume that the PSE is limited to only delivering up to 15.4W. If the Ag59800-LPB detects a Two Event Physical Layer classification, Opto1 will be ON and Opto2 will be OFF. The controller should then assume that the PSE is limited to only delivering up to 30W.

If the PSE does not support the Physical Layer classification, Opto1 and Opto2 will be OFF.

The Ag59800-LPB may operate with some PSEs that are not compliant to the IEEE802.3 specification.

3 Output

3.1 Maximum output power

A Type 4 (IEEE802.3bt) PSE supplying Class 8 power levels shall provide a minimum of 90W at its lowest voltage of 52V from its output, however with cable, connector and rectification losses, the available power and voltage at the input pins of the Ag59800-LPB may be lower than this.

In a fully compliant IEEE802.3 system, the power available, measured at the input to the bridge rectifiers, may be as low as 71.3W, see "ANX-POE-Power" for more details. While the Ag59800-LPB is capable of delivering an output power of 100W, it is recommended that any application where cabling and PSE cannot be specified, be designed for a maximum continuous output power of 67W from the Ag59800-LPB. In applications where cable length or category have additional constraints by the applications requirements or the PSE can be limited to a list of approved models, the available power budget may be higher.

3.2 Output Voltage Adjust Setting

The Ag59800-LPB has an output voltage adjustment pin, ADJ, which can be used to either increase or decrease the output voltage of the module.



Figure 5: Output Voltage Adjustment

Reducing the output voltage, connect RA between ADJ and +VDC							
Value of RA	Ag59812-LPB output	Ag59824-LPB output					
Open Circuit	12.0V	24.0V					
0 Ohms 8.8V 18.9V							
Increasing the o	Increasing the output voltage, connect RA between ADJ and -VDC						
Value of RA	Value of RA Ag59812-LPB output Ag59824-LPB output						
Open Circuit	12.0V	24.0V					
0 Ohms 13.2V 25.0							

Table 5: Output Voltage Adjustment Resistor Values

3.3 Output Filtering

The Ag59800-LPB requires a bulk capacitance to be fitted on its output for stable operation, this is typically provided with a single electrolytic capacitor, this provides a high level of output regulation and low output ripple. Output ripple can be reduced further with the addition of ceramic capacitors across the output. The recommended output filtering is shown in Figure 6.



Figure 6: Output Filter

4 Efficiency

The Ag59800-LPB has been designed as a high efficiency PoE++ solution. In order to preserve this efficiency in the end-to-end solution, it is recommended that the Ag59800-LPB is paired with MOSFET rectification in order to eliminate the voltage drop incurred when using diode-based bridge rectification.



Figure 7: Efficiency

5 Operating Temperature Range

At the heart of the Ag59800-LPB is a DC/DC converter, it will generate heat. While the product has been designed to be a high efficiency device, the small form factor requires that thermal management is taken into consideration at the design stage. The amount of heat generated by the module will depend on the load it is required to drive and the input voltage supplied by the PSE.

The Ag59800-LPB can operate up to a maximum of 85°C ambient, and a minimum of -40°C ambient. When intended for used in ambient temperatures below 0°C it is recommended that an output capacitor that will retain the minimum output capacitance and ESR ratings for the Ag59800-LPB at the lowest temperature in the intended operating range is used. A Polymer Aluminium Electrolytic Capacitor is ideal for this application, however a reputable brand rated to -55°C should suffice for most applications, please contact Silvertel if suggestions are required.

5.1 Thermal Considerations

Each application is different; therefore, it is impossible to give fixed and absolute thermal recommendations. Due to the miniaturised design, while not required, it is recommended that a thermal interface material is used between the module and the host PCB to draw heat out and away from the module for continuous operation. It is recommended to make provision for heatsinking as follows.

The recommended method for drawing heat away from the Ag59800-LPB is by means of copper planes connected to the power pins of the Ag59800-LPB along with a thermal gap filler gel fitted underneath the Ag59800-LPB, such as Parker Chomerics THERM-A-GAP GEL. This technique can be used to draw heat away from the DC/DC converter to dissipate over a larger surface area.

The copper planes should be on the outer layers of the PCB, best results are achieved with additional copper planes on internal layers of host PCB with multiple thermal via connections. An example of this is shown in Figure 8. It is also important that any enclosure has sufficient ventilation for the Ag59800-LPB.

It is recommended that the gap filler is applied to this region such that it encompasses both the components and PCB. The gap filler can be used in combination with thermal via arrays, to reduce the thermal resistance between the copper planes. Figure 9 shows the recommended application area for the gap filler to provide sufficient heat transfer from the module to the host PCB.



Copper Keep out

Thermal Via Array and Gap Filler region

Figure 9: Thermal Interface Application Region

12

Ag59800-LPB

High Efficiency SMT PoE++ Module



V1.2 May 2025

High Efficiency SMT PoE++ Module

Heat dissipation can be improved further by thermally connecting to the enclosure of the application. The simplest method of performing this is to use a thermal gap pad located between the host PCB and the enclosure, situated over the area containing the thermal via arrays.



Figure 10: Additional Heatsinking

V1.2 May 2025

6 Protection

6.1 Input Protection

The Ag59800-LPB will shut down the DC/DC converter if a voltage exceeding the maximum supply rating is detected.

The Ag59800-LPB may be damaged by input voltage transients greater than 80V, while the module contains a TVS diode on board, removing the requirement for fitting external protection in the vast majority of applications. If additional protection from electrostatic discharge (ESD) or other high voltage transients is required, an additional over-voltage clamping device can be fitted across the VIN+ and VIN- input pins, see Figure 11 and Apps Note "ANX-POE-Protection" for more details.



Figure 11: Input Protection

6.2 Output Back Feed Protection

If an external or auxiliary supply is to be used, it is essential that a blocking diode is present to prevent voltage injection on to the output circuitry of the module. This may cause damage to the module. The back feed protection is required even if the external voltage is present only while the module remains unpowered.

6.3 Output Short Circuit Protection

The Ag59800-LPB has over-current protection to prevent the module from becoming damaged in the event of a short circuit event. If an over current event occurs the Ag59800-LPB will disable the output, the Ag59800-LPB will then test the current draw approximately every 2 seconds until the cause of the over current is removed, after which, the power will be restored to the output.

6.4 Thermal Protection

The Ag59800-LPB contains built in thermal protection to prevent the module becoming damaged in the event that it is operated beyond its temperature specification. When the Ag59800-LPB has detected it is over temperature, the output will be disabled until the module has cooled sufficiently.

7 Isolation

To meet the safety isolation requirements of IEEE802.3 specification, a powered device must provide electrical isolation between all its accessible external connectors, including frame ground. In order to meet this requirement, the powered device should be subjected to and pass at least one of the following electrical strength tests of IEC 60950-1:2001 sub clause 6.2.1.

- a) 1500Vrms at 50-60Hz for 60 seconds
- b) $2250V_{dc}$ for 60 seconds or
- c) 1500V $_{dc}$ impulse test 10 times in either polarity.

To assist in this the Ag59800-LPB has been designed to meet and pass the $1500V_{dc}$ impulse test with no breakdown of insulation.

In order to maintain this isolation requirement, it is essential that that the isolation barrier is not breached, see ANX-POE-Isolation-Barrier for more details.

8 EMC

The Ag59800-LPB has been designed to pass EN55032 Class B, however the Ag59800-LPB will only be one component within the system so we would always advise that provisions are put in place in case further noise reductions are needed. From our experience we would recommend an inexpensive but effective solution to reduce emissions as shown in Figure 12, for more details please see ANX-POE-EMI-Considerations.



Figure 12: Typical Connection Diagram

V1.2 May 2025

9 Solderability

The Ag59800-LPB has been designed with a fully automated assembly process in mind and is lead-free (Pb-free) and RoHS compliant and fully compatible with a Pb-free automated assembly process. The Ag59800-LPB can still be mounted manually using soldering iron or hot air.

There are no specific requirements regarding stencil thickness or solder paste classification type. Solder mask defined (SMD) pads are preferred over non-solder mask defined (NSMD) pads, the land pattern dimensions are given in Figure 14.

Minimal thermal relief should be applied to the pads to allow for maximum thermal conductivity without hindering the reflow process, your Process Engineer should be able to provide suitable recommendations.

The Ag59800-LPB requires no components of greater than Moisture Sensitivity level 1, as a result no special processes are required in the reflowing process of the Ag59800-LPB.

9.1 Solder Profile

Below is a typical profile that the Ag59800-LPB should be mounted, based on the J-STD-020 standard for Pb-Free applications. Exceeding these specifications may cause damage to the module. All production environments are different therefore please review these guidelines with the process engineer prior to use.

	Zone 1	Zone 2	Zone 3	Zone 4	Zone 5	Units
Zone Duration	42	42	42	42	42	Seconds
Top Heater	150	180	210	240	270	°C
Bottom Heater	150	180	210	240	270	°C
Typical Slope	2.1	1.2	1.1	0.9	0.8	°C/Second
Airflow rate 40					M ³ /Minute	

Table 6: Solder Profile

	Min	Max	Units
Soak Time (s) 150-180°C	30	90	Seconds
Time above (s) ≥220°C	30	90	Seconds
Peak Temperature (°C)	230	255	°C
∆Temperature (°C/s)	-3	3	°C/Second

Table 7: Solder Parameters

Note : Do not pass the Ag59800-LPB through the reflow process mounted to the underside of the assembly due to the risk of components falling off the module.

10 Electrical Characteristics

10.1 Absolute Maximum Ratings

	Parameter	Symbol	Min	Max	Units
1	DC Supply Voltage	Vcc	-0.3	60	V
2	Storage Temperature	Ts	-40	+100	°C
3	Moisture Sensitivity Level	MSL	-	1	-

Note : Exceeding the above ratings may cause permanent damage to the product. Functional operation under these conditions is not implied. Maximum ratings assume free airflow.

10.2 Recommended Operating Conditions

	Param	eter	Symbol	Min	Тур	Max	Units
1	Input Suppl	y Voltage	Vin	41 ¹	54	57	V
2	Transient Supply Voltage ¹		Vtran	36			V
3	Input Under Voltage Lockout		Vulock		37		V
4	Under Voltage Lockout Hysteresis		VULOCK-Hsy		2.5		V
5	Operating Temperature		T _{OP}	-40	25	85	Ta / °C
6	Output capacitance	Ag59812-LPB	Court	470	1000	1500	μF
	Ag59824-LPB			330	470	680	•

Note 1: With less than 50% load

V1.2 May 2025

High Efficiency SMT PoE++ Module

10.3 DC Electrical Characteristics

	DC Characteristic		Sym	Min	Typ1	Max	Units	Comments
1	Nominal Output Voltage	Ag59812-LPB	+Vout	11.5	12	12.5	V	
		Ag59824-LPB		23.25	24	24.8		
2	Continuous Current output ²	Ag59812-LPB	I _{LOAD}		8	8.4	A	
		Ag59824-LPB			4	4.2		
3	Line Regulation		VLINE1		0.01		%	@ 50% load
4	Load Regulation		VLOAD1		0.08		%	
5	Ripple and Noise ²	Ag59812-LPB	V _{RN}		75		• mV _{p-p}	At Full Load
		Ag59824-LPB			100			
6	Minimum Load		I _{MIN}	0			mA	
7	Short-Circuit Duration		Tsc			∞	sec	
8	Peak Efficiency ³	Ag59812-LPB	EFF		95.0		%	
		Ag59824-LPB			93.8			
9	Isolation Voltage (I/O)		Viso			1500	Vрк	Impulse Test

Note 1: Typical figures are at 25°C with a nominal output voltage with 57V supply with a 470µF output capacitor fitted and are for design aid only. Not Guaranteed.

Note 2: Measured with recommended output filter, see Section 3.3.

Note 3: Minimum 44Vin for maximum output at 25°C. Maximum output power may be limited by PSE.

V1.2 May 2025

11 Package



Figure 13: Package Dimensions



Figure 14: Land Pattern

V1.2 May 2025

12 Packaging

The default packing for the Ag59800-LPB series is supplied in trays of TBC.

13 Ordering Code



blank = Tray, 15TR = 15" Reel



Singel 3 | B-2550 Kontich | Belgium | Tel.+32(0)3 458 30 33 nfo@alcom.be | www.alcom.be Rivium 1e straat 52 | 2909 LE Capelle aan den Ussel | The Netherlands A STELIAU TECHNOLOGY COMPANY Tel.+31(0)10 288 25 00 | info@alcom.nl | www.alcom.nl

Information published in this datasheet is believed to be correct and accurate. Silver Telecom assumes no liability for errors which may occur or for liability otherwise arising out of use of this information or infringement of patents which may occur as a result of such use. No license is granted by this document under patents owned by Silver Telecom or licensed from third parties by Silver Telecom. The products, their specification and information appearing in this document are subject to change by Silver Telecom without notice.